

# TRADESWITCH4-USB

KVM switches, Article number A2100080



Front



Back

With the KM switch TradeSwitch4, you can operate up to four computers over only one set of keyboard/mouse. The switch does not process video signals. Each workplace monitor is directly connected to the computer and permanently displays its image.

## SCOPE OF DELIVERY

| Quantity | Description                             | Article number |
|----------|---|----------------|
| 8        | Audio-M/M-2-ferrite cable 2m            | A6300083       |
| 4        | USB-AM/BM-2 cable USB 2m                | A6300113       |
| 1        | PowerCable-2 Standard cable 2m          | A6300057       |
| 1        | USB-Service-2 cable 2m                  | A6200103       |
| 1        | Safety instructions flyer - FCC class B | A9100371       |

## DETAILS

### VIDEO

- The TradeSwitch does not process video signals. Each monitor of the user console is directly connected to the computer and permanently displays its image.

### SIGNALS

- Stereo audio signals
- USB 2.0 with hi-speed, all USB classes

### DEVICE

- Accesses as hardware switch only the standard interfaces keyboard, mouse and audio
- Access to standard interfaces of the computer, with no software installation required
- Internal power pack for main power supply

### SYSTEM UPDATE

- Flash upgrade via the device

### WARRANTY

- A 3-year, free of charge product guarantee
- For an additional fee guarantee extension possible

## FEATURES

### OPERATION FEATURES

- With the TradeSwitch, you can operate several computers over only one set of keyboard/mouse.
- Switching between computers is done either via the buttons on the front of the TradeSwitch, via configurable key combinations on the keyboard or via a serial device.
- Ready for operation out of the box, no additional configuration required
- Permanent keyboard/mouse emulation ensures a stable system

### CONTROL OPTIONS

- CrossDisplay-Switching: The mouse acts as if on a “virtual desktop” and can be moved seamlessly across the connected displays. Moving the cursor from the active to another display, the keyboard-mouse focus automatically switches to the connected computer. This feature lets you create multi-monitor workplaces, where users do not have to deal with the actual infrastructure. Thus, they are able to perform their tasks while operating the system intuitively. The mouse becomes the ultimate intuitive switching tool.



## EXTENSIONS

### DEVICE

- Attach the optional LED sets to the monitors. This facilitates locating the monitor (computer) to which the keyboard/mouse focus is switched to.

## TECHNICAL DATA

|               |                                |                                   |
|---------------|--------------------------------|-----------------------------------|
| General       | Product group                  | KVM switches                      |
|               | Product Family                 | TradeSwitch                       |
|               | Number of workstations         | 1                                 |
|               | Number of sources              | 4                                 |
|               | Power Supply                   | no redundancy                     |
| Input options | USB mouse                      | yes                               |
|               | USB keyboard                   | yes                               |
| Audio         | Transmission type              | Stereo                            |
|               | Bandwidth                      | 22 kHz                            |
|               | Audio support                  | Analog                            |
| USB           | Separate USB transmission port | no                                |
|               | Specification                  | USB 2.0                           |
|               | Transmission rate              | max. 480 Mbit/s (Hi-Speed)        |
|               | Range                          | max. 5 m                          |
|               | Power (output)                 | 500 mA (HighPower)                |
|               | USB classes                    | All                               |
| Maintenance   | Update via                     | Update Wizard (service interface) |
|               | Serviceport settings           | 115200bps (8/N/1)                 |
| Housing       | Material                       | Anodised aluminium                |

|                      |  |   |
|----------------------|--|---|
|                      | Width ca.                                  | 270 mm  |
|                      | Height ca.                                 | 44 mm   |
|                      | Depth ca.                                  | 210 mm  |
|                      | IP protection class                        | IP20  |
|                      | Weight ca.                                 | 1.4 kg  |
| Operating conditions | Operating environment temperature          | 5 °C to 45 °C   |
|                      | Operating air humidity, non-condensing     | 20 % to 80 %  |
|                      | Area of application                        | Indoor use  |
|                      | Maximum operating altitude above sea level | 3,048 m   |
|                      | Storage environment temperature            | -10 °C to 55 °C   |
|                      | Storage air humidity, non-condensing       | 15 % to 85 %  |
|                      | MTBF                                       | 185,000 h at 25°C   |
|                      | Conformities                               | CE compliant (see downloads)<br>UKCA compliant (see downloads)<br>FCC compliant (see manual)<br>TAA compliant (see downloads)<br>EAC compliant (see downloads)<br>RoHS compliant (see downloads)<br>WEEE (reg. no. DE30763240)<br>REACH compliant (see downloads) |
| Power supply         | Quantity                                   | 1   |
|                      | Type                                       | Internal  |
|                      | Input voltage                              | 100-240 VAC   |

|  |                        |             |
|--|------------------------|-------------|
|  | Input frequency        | 60-50 Hz    |
|  | Current consumption    | 0.21-0.12 A |
|  | Power consumption idle | 1.8-2.3 W   |
|  | Power consumption max. | 10.4-11 W   |
|  | Heat output idle       | 1.8-2.3 W   |
|  | Heat output max.       | 4.4-5 W     |

## ACCESSORY PRODUCTS

| Image   | Description  | Article number |
|---|--|----------------|
|    | <b>Audio-M/M-3-ferrite cable 3m</b><br>Audio connection cable with ferrite core                                | A6300118       |
|    | <b>Audio-M/M-5-ferrite cable 5m</b><br>Audio connection cable with ferrite core                                | A6300085       |
|    | <b>PowerCable-3 Standard cable 3m</b><br>Cable to connect the power supply type Germany                        | A6300066       |
|    | <b>PowerCable-5 Standard cable 5m</b><br>Cable to connect the power supply type Germany                        | A6300065       |
|    | <b>USB-AM/BM-3 cable USB 3m</b><br>USB cable, Type-A Plug/Type-B Plug  | A6300114       |
|  | <b>USB-AM/BM-5 cable USB 5m</b><br>USB cable, Type-A Plug/Type-B Plug  | A6300111       |
|  | <b>19" RM-Set-270-1RU</b><br>19" extension for rack mounting devices of 270 mm width within 1RU (44 mm height) | A7000023       |

## RELATED PRODUCTS

| Description   | Article number |
|---|----------------|
| <b>TS-LED-blue-2</b><br>LED to tag the active console of a TradeSwitch configuration of a matrix, resp. the active channel of a TradeSwitch | A6100168       |
| <b>TS-LED-blue-3</b><br>LED to tag the active console of a TradeSwitch configuration of a matrix, resp. the active channel of a TradeSwitch | A6100169       |
| <b>TS-LED-blue-5</b><br>LED to tag the active console of a TradeSwitch configuration of a matrix, resp. the active channel of a TradeSwitch | A6100170       |

# CONTACT

## WE ARE HERE FOR YOU!

If you have any further questions, we are looking forward to advising you on your individual project requirements.

### TECHNICAL SALES

Tel.: +1-833-928-1976  
Fax: +1-833-928-1976  
E-Mail: [sales.us@gdsys.com](mailto:sales.us@gdsys.com)

### HEADQUARTERS

Guntermann & Drunck GmbH Systementwicklung  
Obere Leimbach 9 | 57074 Siegen | NRW |  
Deutschland

Tel.: +49 271 23872-0  
Fax: +49 271 23872-120  
E-Mail: [sales@gdsys.com](mailto:sales@gdsys.com)

### US OFFICE

G&D North America Inc.  
4540 Kendrick Plaza Drive | Suite 100  
Houston, TX 77032 | United States

Tel.: +1-346-620-4362  
E-Mail: [sales.us@gdsys.com](mailto:sales.us@gdsys.com)

### MIDDLE EAST OFFICE

Guntermann & Drunck GmbH  
Dubai Studio City | DSC Tower  
12th Floor, Office 1208 | Dubai, UAE

Tel.: +971 4 5586178  
E-Mail: [sales.me@gdsys.com](mailto:sales.me@gdsys.com)

### APAC OFFICE

Guntermann & Drunck GmbH  
60 Anson Road #17-01  
Singapore 079914

Tel.: +65 9685 8807  
E-Mail: [sales.apac@gdsys.com](mailto:sales.apac@gdsys.com)